

# GTM ELECTRONICS

## SOD-323 Zener Diodes

Part No.	Nominal Zener Voltage	Test Current	Maximum Zener Impedance	Maximum Zener Impedance	Maximum Reverse Current		Marking Code
	Vz	Izt	Zzt@Izt	Zzk@Izk=0.25mA	Ir	@VR	
	V	mA	Ω	Ω	uA	V	
GDMBZ5221B	2.4	20	30	1200	100	1.0	1A
GDMBZ5222B	2.5	20	30	1250	100	1.0	1B
GDMBZ5223B	2.7	20	30	1300	75	1.0	1C
GDMBZ5224B	2.8	20	30	1400	75	1.0	1D
GDMBZ5225B	3.0	20	29	1600	50	1.0	1E
GDMBZ5226B	3.3	20	28	1600	25	1.0	8A
GDMBZ5227B	3.6	20	24	1700	15	1.0	8B
GDMBZ5228B	3.9	20	23	1900	10	1.0	8C
GDMBZ5229B	4.3	20	22	2000	5.0	1.0	8D
GDMBZ5230B	4.7	20	19	1900	5.0	2.0	8E
GDMBZ5231B	5.1	20	17	1600	5.0	2.0	8F
GDMBZ5232B	5.6	20	17	1600	5.0	3.0	8G
GDMBZ5233B	6.0	20	7.0	1600	5.0	3.5	8H
GDMBZ5234B	6.2	20	7.0	1000	5.0	4.0	8J
GDMBZ5235B	6.8	20	5.0	750	3.0	5.0	8K
GDMBZ5236B	7.5	20	6.0	500	3.0	6.0	8L
GDMBZ5237B	8.2	20	8.0	500	3.0	6.5	8M
GDMBZ5238B	8.7	20	8.0	600	3.0	6.5	8N
GDMBZ5239B	9.1	20	10	600	3.0	7.0	8P
GDMBZ5240B	10	20	17	600	3.0	8.0	8Q
GDMBZ5241B	11	20	22	600	2.0	8.4	8R
GDMBZ5242B	12	20	30	600	1.0	9.1	8S
GDMBZ5243B	13	9.5	13	600	0.5	9.9	8T
GDMBZ5244B	14	9.0	15	600	0.1	10	8U
GDMBZ5245B	15	8.5	16	600	0.1	11	8V
GDMBZ5246B	16	7.8	17	600	0.1	12	8W
GDMBZ5247B	17	7.4	19	600	0.1	13	8X
GDMBZ5248B	18	7.0	21	600	0.1	14	8Y
GDMBZ5249B	19	6.6	23	600	0.1	14	8Z
GDMBZ5250B	20	6.2	25	600	0.1	15	2A
GDMBZ5251B	22	5.6	29	600	0.1	17	2B
GDMBZ5252B	24	5.2	33	600	0.1	18	2C
GDMBZ5253B	25	5.0	35	600	0.1	19	2D
GDMBZ5254B	27	4.6	41	600	0.1	21	2E
GDMBZ5255B	28	4.5	44	600	0.1	21	2F
GDMBZ5256B	30	4.2	49	600	0.1	23	2G
GDMBZ5257B	33	3.8	58	700	0.1	25	2H
GDMBZ5258B	36	3.4	70	700	0.1	27	2J
GDMBZ5259B	39	3.2	80	800	0.1	30	2K
GDMBZ5260B	43	3.0	93	900	0.1	33	2L
GDMBZ5261B	47	2.7	105	1000	0.1	36	2M
GDMBZ5262B	51	2.5	125	1100	0.1	39	2N
GDMBZ5263B	56	2.2	150	1300	0.1	43	2P
GDMBZ5264B	60	2.1	170	1400	0.1	46	2Q
GDMBZ5265B	62	2.0	185	1400	0.1	47	2R
GDMBZ5266B	68	1.8	230	1600	0.1	52	2S
GDMBZ5267B	75	1.7	270	1700	0.1	56	2T
GDMBZ5268B	82	1.5	330	2000	0.1	62	2U
GDMBZ5269B	87	1.4	370	2200	0.1	68	2V
GDMBZ5270B	91	1.4	400	2300	0.1	69	2W

量產	未量產	有樣品	工程實驗未產出
----	-----	-----	---------